

Boost Box Setup Guide

Thank you for your purchase of an Advantage Boost Box™!

What's included

- (1) Boost Box[™] by Advantage Software, Inc.
- (1) Power adapter
- (1) RJ45 Crossover cable (labeled)

Before beginning please note that your Boost Box was shipped with an RJ45 Crossover cable. This looks like a standard ethernet cable, but it has a special wiring configuration and cannot be used for regular internet connectivity purposes. For this reason, the Crossover cable has been clearly marked for your convenience.

If you misplace your Crossover cable, another can be purchased from Advantage.


- Step 1: Insert the power cable into your Boost Box into the power input port labeled DC
- Step 2: Plug the included crossover cable into the LAN port
- Step 3: Plug the Crossover cable into your Eclipse PC
- Step 4: Power the Boost Box on using the red power button



Windows Network Settings

To access Boost Box settings in Windows


- Right-click on the network icon in the lower right corner
- Choose Open Network & Internet Settings




 Choose Change adapter options in the advanced network settings section.
 A new window will appear.

Advanced network settings Change adapter options View network adapters and change connection settings.


 Identify the Boost Box LAN connection to your PC, most computers only have one LAN/Ethernet port.



• Double-click on the LAN/Ethernet network and then choose Properties



Double-click on Internet Protocol Version 4)TCP/IPv4)



Set Boost Box IP addresses

Obtain an IP address automatically
 Use the following IP address:

• Step 1: Choose Use the following IP address

(note that you do not need to type the . in manually. Use the right arrow to move from 0 to the space for 2)

• Step 2: Set the IP address field to

192.168.101.2

IP address:			
Subnet mask:			
Default gateway:			

ODbtain an IP address automatically

-0	Use	the	followina	IΡ	address:	
	030	u	1010Willing	1 1	ada caa.	

IP address:	192 . 168 . 101 . 2
S <u>u</u> bnet mask:	
Default gateway:	

• Step 3: Press **Tab** to autofill the Subnet mask

Obtain an IP address automatically

• Use the following IP address:

IP address:	192 . 168 . 101 . 2
S <u>u</u> bnet mask:	255 . 255 . 255 . 0
Default gateway:	

• Use the following IP address:

IP address:	192.168.101.2
S <u>u</u> bnet mask:	255 . 255 . 255 . 0
Default gateway:	192 . 168 . 101 . 1

- Step 4: Set the Default gateway to 192.168.101.1
- Press OK to save these changes.

Eclipse Settings

- Open Eclipse
- Navigate to User Settings (Alt+U)→Translate tab
- Click on Boost

User settin	gs			×
User Input	Paragraphs Realtime	Docume Translate	nt Edit Numbers	Display Programming
*	Untran borders	: KPH-F	L	
Phone	etic untranslates	Basic	~ 🗆 S	uppress untrans
Tie related items				
Insert missing BY Suppress dou <u>b</u> le paragraphs				
Convert ANSWER to THE WITNESS				
Pick 1st conflict by default Translation Magic Boost				
Make	edit station info			

 \times

Setup..

Cancel

Al Boost settings

<mark>∕ <u>B</u>oost</mark>

Boost <u>F</u>low

ОК

- Check Boost
- Check **Boost Flow** if desired
- Set Engine to Speechmatics
- Click on Setup...
- In the Speech options setup window, choose **SpeechMatics**

Use dictation <u>m</u> ode				
Use <u>r</u> ealtime timecodes				
Start with microphone on				
OK Speech <u>M</u> atics Cancel				

Engine Speechmatics

Flow commands.. Exceptions..

 \sim

50%

• Next, choose IP address and press OK

Pick one:	×	
Check minutes		
IP address		
Account ID		
Speech model		
Max delay		
Delay mode		
ОК	Cancel	
*		
Enter text:IP address		

• Set the IP address to ws://192.168.101.1 and press OK

٠	
Enter text:IP add	ress
ws://192.16	8.101.1
ОК	